

# EX-714 Stereo System 2x45W into 8Ω - Bluetooth

## HIGHLIGHTS

- ✓ Bluetooth function
- ✓ Coaxial & Optical inputs
- ✓ Sub output
- ✓ CD/USB/AM/FM/DAB
- ✓ MP3 input
- ✓ Headphone output

## LOGISTICAL DATA

**EAN Code**  
Black: 0634654606006

**DEEE**  
4.4 = 0,84 € H.T. = 1 € T.T.C.

**Dimensions (WxHxD) & Weight PRODUCT**  
434 x 104 x 355 mm / 10,7 Kg

**PACKAGING**  
498 x 174 x 445 mm / 11,5 Kg



**Front panel**  
Treble knob: 10Hz +/-8dB  
Bass knob: 100Hz +/-8dB  
Balance: yes

The EX-714 integrated hi-fi system was designed on the basis of the EX-712.2, which has been acclaimed on numerous occasions, notably by Classica magazine, which awarded it a « Choc », and by qobuz for a « qobuzissime ».

The EX-714 delivers a power of 2x45W RMS under 8 Ohms and thanks to its ultra powerful power supply (220VA toroidal transformer), it increases to 2x70W under 4 Ohms. The CD player is now Slot-in type (MP3/WMA) and the FM/AM Tuner is now equipped with digital radio (DAB) with 40 memorised stations. Its USB port allows you to play your digital files stored on a USB key in MP3 and WMA formats.

Its Bluetooth receiver allows you to listen to music from your tablets and smartphones. It has an auxiliary analogue input (RCA) and a digital input (optical and coaxial) allowing it to be connected to the latest generation of TV sets.

The EX-714 also offers a subwoofer output for connecting an active subwoofer.

### MAIN FEATURES

- High quality manufacturing
- Shielded preamplifier
- Large power supply
- Bluetooth connection with integrated antenna
- Optical and coaxial digital inputs
- Phono input (MM cartridge)
- MP3 input
- 6.35mm headphone output

### Included Accessories

- 1x Detachable IEC power cord
- 1x Remote control
- 2x Batteries
- 1x DAB Antenna
- 1x FM Antenna
- 1x AM Antenna
- 1x Manual

**Digital Inputs:** The OPTICAL connector will override the source connected to COAXIAL, unless the source connected to the optical connector is turned off. In this case, you can listen to the source connected in coaxial.

## SPECIFICATIONS

### Amplifier section

Power: 2x45W RMS into 8 Ω  
and 2x70W into 4 Ω  
Total harmonic distortion < 0,01%  
Signal to noise ratio > 100 dBA  
Bandwidth: 20 Hz - 20 KHz  
Analog max. input: 3,5V  
Speaker Impedance: 4-8 Ω

### Bluetooth 5.0 (Wireless)

Range: about 10 m (unobstructed)

### Connectors

- 1x USB Entry (front)
- Line Input (RCA)
- 1x PHONO Entry (MM) (RCA)
- 1x Coaxial Digital Entry (RCA)
- 1x Optical Digital Entry
- 1x Subwoofer Output (RCA)
- 1x headphone Output (6,35mm jack)
- 1x Embedded Bluetooth Antenna
- 1x DAB Antenna
- 1x FM Antenna
- 1x AM Connector
- 4x Speaker Screw terminals compatible with banana plugs
- 1x Power socket

### Phono input

Input impedance: 47 KΩ  
Gain: 40dB  
Harmonic Distortion <0.005%  
(1kHz, 1W, 8Ω)  
Frequency band: 10Hz - 20KHz  
(± 0.2dB of RIAA)

CD Mechanism : TMC688  
DAB : Verona 2 FS2445B  
DAC : PCM1606E (24BIT 192kHz)